



Z-Wave Protocol Implementation Conformance Statement

Z-Wave Interface Module

General Information

Product Identifier:	Pro.zwi.us
Brand Name:	Pro Control
Product Version:	HW: 193 FW: 4.36:01.01
Z-Wave Certification #:	ZC10-16085178

Product Features

Color	White
Communications Connections	Ethernet (Wired)
Controller Supports Multiple Networks	No
Controller Supports Multiple Z-Wave Interfaces	No
Firmware Updatable	Updatable by Consumer by Wire
IP (Ingress Protection) Rated	No
Outdoor Use	No

Z-Wave Product Information

Supports Z-Wave Beaming Technology?	Yes
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	Yes
Supports Security S2?	No
SmartStart Compatible?	No

Z-Wave Protocol Implementation Conformance Statement

(Continued)

Z-Wave Interface Module

Z-Wave Technical Information

Z-Wave Frequency:	U.S. / Canada / Mexico
Z-Wave Product ID:	0x0001
Z-Wave Product Type:	0x0001
Z-Wave Hardware Platform:	ZM5304
Z-Wave Development Kit Version:	6.51.07
Z-Wave Library Type:	Static Controller
Z-Wave Device Type / Role Type:	Gateway / Central Static Controller

Association Group Information

Group # / Max Description

Nodes

1 / 1 Z-Wave Plus Lifeline

Supported Command Classes (10):

Application Status	Association Group Information V2
Association V2	CRC16 Encapsulation
Device Reset Locally	Manufacturer Specific V2
Powerlevel	Security S0
Version V2	Z-Wave Plus Info V2

Controlled Command Classes (37):

Association Group Information V2	Association V2
Barrier Operator	Basic V2
Battery	Configuration V3
CRC16 Encapsulation	Door Lock V3
Indicator	Manufacturer Specific V2
Meter V4	Multi-Channel Association V3
Multi-Channel V4	Network Management Basic
Network Management Inclusion	Network Management Primary
Network Management Proxy	No Operation
Notification V3	Powerlevel
Scene Activation	Scene Actuator Conf
Scene Controller Conf	Security S0
Switch All	Switch Binary V2
Switch Multilevel V4	Thermostat Fan Mode V4
Thermostat Fan State V2	Thermostat Mode V3
Thermostat Operating State V2	Thermostat Setpoint V3
Time Parameters	Time V2
User Code	Version V2
Wake Up V2	